



LUMAG GmbH • Rudolf-Diesel-Straße 1a • 84375 Kirchdorf/Inn
 Telefon: +49 (0)8571/92556-0 • Fax: +49 (0)8571-92556-19
info@lumag-maschinen.de • www.lumag-maschinen.de

G8-E

Petrol Generator with E-Start & remote control

PRODUCT-INFORMATION

Technische Data Generator G8-E

Gasoline synchronous generator with 100% copper wire

Max. Output	8,0 kW
Continuous Power Output	7,0 kW
Connection	3 x 230V / 16A, 1 x 400V / 16A
Frequency	50 Hz
Starting System	Recoil, E-Start, Remote Start
Dimensions (L/W/H)	870 / 585 / 620 mm
Weight (net / gross)	96 / 118 kg
Packaging Dimensions (L/B/H)	890 / 600 / 640 mm

Technische Data Engine KB 192F

Engine-Type	4-stroke OHV Petrol Engine
Max. Nominal Power	9,5 kW bei 3.600 U/min
Max. Torque	92 Nm bei 2.500 U/min
Displacement	440 cm ³
Volumen Oiltank	1,1 Liter
Volumen Fuel Tank	25 Liter
Dimensions (L/W/H)	710 / 540 / 580 mm
weight	96 kg

Generator with
100% copper wire



Art. Nr.: G8E

EAN: 40 47424 00489 0



Equipment features:

- 4-stroke OHV gasoline engine
- Oil low - automatic shutdown
- Generator overload protection
- Hour meter and tank level indicator
- Starter battery 12V
- Folding carrying handles for easy transport
- Starting system with reversing starter, electric starter and remote start
- 3 x 230V, 1 x 400V